

# RXM23K-RXM28

2 CHANNELS UNIVERSAL RECEIVERS 433 MHz AND 868 MHz



## ELECTRICAL DATA

reception frequency <b>RXM23K</b>	MHz	433,920
reception frequency <b>RXM28</b>	MHz	868,3
feed with inserted jumper	Vac	12-14
	Vdc	10-16
feed with jumper not inserted	Vac	14-24
	Vdc	16-35
maximum consumption with both relays active	mA	70
maximum relay contact current	A	1

## GENERIC DATA

protection degree	IP	30
dimensions (L - D - H)	mm	85 - 40 - 25
operating temperature	°C	-20 + 50

## MODELS

CODE	DESCRIPTION
<b>RXM23K</b>	Universal receiver 2 channels, fix or rolling code, 1000 codes 433 MHz
<b>RXM28</b>	Universal 2-channel receiver, rolling code, 1000 code memory, 868 MHz