

## MEDIA PLAYER AMPLIFIERS

# MPA Media Player Amplifiers

Media amplifiers with integrated music player.

# MPA 30

MPA 30 - mixing media amplifier with integrated USB and SD MMC card player/recorder and FM radio tuner. Audio signal mixing, low and high impedance outputs, priority input and tone control. Preamp output and preamp input. Recording function is performed on memory cards or USB Flash drive. Selectable gain (AUX/ Phono), stereo RCA input. No need for professional installation assistance, and it's so easy to use. The MPA 30 supports compressed audio files and is an excellent device for small size applications where amplification with music source and audio signal mixing is required.

With external 12V DC power supply capability.



Technical Specifications	MPA 30
Output power	30W
AC power consumption	60VA
Power supply	~230V/50Hz or 12V DC
Outputs	Low impedance output- 4 Ω (Screw terminal connectors) Hi impedance outputs- 25 V,70 V, 100 V (Screw terminal connectors) Preamp Out - output level 0 dBu
Inputs	MIC: Sensitivity- 47 dBu Priority Input - MIC 1 Connectors- Unbalanced TS 6.3mm jack AUX/PHONO: Sensitivity- 17 dBu (when switch is set to AUX position) Sensitivity- 47 dBu (when switch is set to PHONO position) Connector- RCA AMP input: Sensitivity - 0 dBu Connector- RCA
Frequency response	80 Hz -18 kHz
Tone control	Bass ±12 dB, Treble ±12 dB
THD	< 0,5%
Signal/ noise ratio	>75 dB
Controls	MIC and AUX/PHONO input level controls, tone control, USB SD MMC card player volume control, master volume control
Indicators	Power
Dimensions	280 mm x 190 mm x 75 mm
Weight	4,5 kg